



SLASH72W

18×3W 3IN1 (RGB) OUTDOOR PIXEL BAR

USER MANUAL



MADE IN CHINA



1.KEY AND DISPLAY FUNCTIONS

1.1. Key instruction



MENU: Table1 function loops add;
 UP: function value add;
 DOWN: function value decrease;
 ENTER: save the setting;

1.2. Display instruction

No.	Show	Value	Function
1	d001	001 - 512	DMX512 Address
2	R255	000 - 255	Red Dimming, From dark to light
3	G255	000 - 255	Green Dimming, From dark to light
4	B255	000 - 255	Blue Dimming, From dark to light
5	FF99	00 - 99	RGB Strobe, Speed from slow to fast
6	1JP0	0 - 9	Jump effect 01,Speed from slow to fast
7	2JP0	0 - 9	Jump effect 02,Speed from slow to fast
8	3JP0	0 - 9	Jump effect 03,Speed from slow to fast
9	4JP0	0 - 9	Jump effect 04,Speed from slow to fast
10	5JP0	0 - 9	Jump effect 05,Speed from slow to fast
11	6JP0	0 - 9	Jump effect 06,Speed from slow to fast
12	7JP0	0 - 9	Jump effect 07,Speed from slow to fast
13	8JP0	0 - 9	Jump effect 08,Speed from slow to fast
14	9JP0	0 - 9	Loops jump effect 01 to 08
15	1dE0	0 - 9	Red shade effect, Speed from slow to fast
16	2dE0	0 - 9	Green shade effect ,Speed from slow to fast
17	3dE0	0 - 9	Blue shade effect, Speed from slow to fast
18	4dE0	0 - 9	Pink shade effect, Speed from slow to fast
19	5dE0	0 - 9	Yellow shade effect ,Speed from slow to fast
20	6dE0	0 - 9	Loops red to yellow shade effect ,Speed



Timpani S.r.L.
 Via Idiomi 1/42 - 20090 Assago MI
 timpani.it

+39 051.356956

+39 342.3929868

info@timpani.it



CH49	000-255	16# Green Dimming, From dark to light
CH50	000-255	16# Blue Dimming, From dark to light
CH51	000-255	17# Red Dimming, From dark to light
CH52	000-255	17# Green Dimming, From dark to light
CH53	000-255	17# Blue Dimming, From dark to light
CH54	000-255	18# Red Dimming, From dark to light
CH55	000-255	18# Green Dimming, From dark to light
CH56	000-255	18# Blue Dimming, From dark to light

3.SPECIFICATIONS:

Input voltage: AC100V/240V 50/60HZ

Power: 80W

Light source: 18x3W RGB 3IN1 LED

Control mode : DMX512, master-slave,Sound

DMX Channel: 2/3/5/6/8/9/18/54/56CH

IP Rate: IP65

Net weight: 4KG

Package Size: 1070(L) x 140 (W) x180(H)mm



			from slow to fast
21	Sud0	0 - 9	Sound active, Speed from slow to fast
22	CH02	02/03/05/06/08/09/18/54/56	DMX channel mode set

2.DMX512 Configuration

2 Channels Mode:

Channel	DMX Value	Function
CH1	000-005	Null
	006-016	Red
	017-027	Green
	028-038	Blue
	039-049	Yellow
	050-060	Pink
	061-071	Cyan
	072-082	White
	083-093	Jump effect 01
	094-104	Jump effect 02
	105-115	Jump effect 03
	116-126	Jump effect 04
	127-137	Jump effect 05
	138-148	Jump effect 06
	149-159	Jump effect 07
	160-170	Jump effect 08
	171-181	Loops jump effect 01 to 08
	182-192	Red shade effect
	193-203	Green shade effect
	204-214	Blue shade effect
215-225	Pink shade effect	
226-236	Yellow shade effect	
237-247	Loops red to yellow shade effect	
248-255	Sound active	
CH2	000-255	Speed from slow to fast



3 Channels Mode:

Channel	DMX Value	Function
CH1	000-255	Red Dimming, From dark to light
CH2	000-255	Green Dimming, From dark to light
CH3	000-255	Blue Dimming, From dark to light

5 Channels Mode:

Channel	DMX Value	Function
CH1	000-255	RGB Total Dimming, From dark to light
CH2	000-255	Red Dimming, From dark to light
CH3	000-255	Green Dimming, From dark to light
CH4	000-255	Blue Dimming, From dark to light
CH5	007-255	RGB Strobe, Speed from slow to fast

6 Channels Mode:

Channel	DMX Value	Function
CH1	000-255	1-8# Red Dimming, From dark to light
CH2	000-255	1-8# Green Dimming, From dark to light
CH3	000-255	1-8# Blue Dimming, From dark to light
CH4	000-255	9-18# Red Dimming, From dark to light
CH5	000-255	9-18# Green Dimming, From dark to light
CH6	000-255	9-18# Blue Dimming, From dark to light

8 Channels Mode:

Channel	DMX Value	Function
CH1	000-255	RGB Total Dimming, From dark to light
CH2	007-255	RGB Strobe, Speed from slow to fast
CH3	000-005	Null
	006-015	Customize effect 1#--13#;
	016-025	CH1: dimming
	026-035	CH2 superimposed strobe effect;
	036-045	CH5 select background colors;
	046-055	CH6-CH8: select effect colors;



CH16	000-255	5# Green Dimming, From dark to light
CH17	000-255	5# Blue Dimming, From dark to light
CH18	000-255	6# Red Dimming, From dark to light
CH19	000-255	6# Green Dimming, From dark to light
CH20	000-255	6# Blue Dimming, From dark to light
CH21	000-255	7# Red Dimming, From dark to light
CH22	000-255	7# Green Dimming, From dark to light
CH23	000-255	7# Blue Dimming, From dark to light
CH24	000-255	8# Red Dimming, From dark to light
CH25	000-255	8# Green Dimming, From dark to light
CH26	000-255	8# Blue Dimming, From dark to light
CH27	000-255	9# Red Dimming, From dark to light
CH28	000-255	9# Green Dimming, From dark to light
CH29	000-255	9# Blue Dimming, From dark to light
CH30	000-255	10# Red Dimming, From dark to light
CH31	000-255	10# Green Dimming, From dark to light
CH32	000-255	10# Blue Dimming, From dark to light
CH33	000-255	11# Red Dimming, From dark to light
CH34	000-255	11# Green Dimming, From dark to light
CH35	000-255	11# Blue Dimming, From dark to light
CH36	000-255	12# Red Dimming, From dark to light
CH37	000-255	12# Green Dimming, From dark to light
CH38	000-255	12# Blue Dimming, From dark to light
CH39	000-255	13# Red Dimming, From dark to light
CH40	000-255	13# Green Dimming, From dark to light
CH41	000-255	13# Blue Dimming, From dark to light
CH42	000-255	14# Red Dimming, From dark to light
CH43	000-255	14# Green Dimming, From dark to light
CH44	000-255	14# Blue Dimming, From dark to light
CH45	000-255	15# Red Dimming, From dark to light
CH46	000-255	15# Green Dimming, From dark to light
CH47	000-255	15# Blue Dimming, From dark to light
CH48	000-255	16# Red Dimming, From dark to light



CH40	000-255	14# Red Dimming, From dark to light
CH41	000-255	14# Green Dimming, From dark to light
CH42	000-255	14# Blue Dimming, From dark to light
CH43	000-255	15# Red Dimming, From dark to light
CH44	000-255	15# Green Dimming, From dark to light
CH45	000-255	15# Blue Dimming, From dark to light
CH46	000-255	16# Red Dimming, From dark to light
CH47	000-255	16# Green Dimming, From dark to light
CH48	000-255	16# Blue Dimming, From dark to light
CH49	000-255	17# Red Dimming, From dark to light
CH50	000-255	17# Green Dimming, From dark to light
CH51	000-255	17# Blue Dimming, From dark to light
CH52	000-255	18# Red Dimming, From dark to light
CH53	000-255	18# Green Dimming, From dark to light
CH54	000-255	18# Blue Dimming, From dark to light

56Channels Mode:

Channel	DMX Value	Function
CH1	000-255	RGB Total Dimming, From dark to light
CH2	007-255	RGB Strobe,SPEED FROM SLOW TO FAST
CH3	000-255	1# Red Dimming, From dark to light
CH4	000-255	1# Green Dimming, From dark to light
CH5	000-255	1# Blue Dimming, From dark to light
CH6	000-255	2# Red Dimming, From dark to light
CH7	000-255	2# Green Dimming, From dark to light
CH8	000-255	2# Blue Dimming, From dark to light
CH9	000-255	3# Red Dimming, From dark to light
CH10	000-255	3# Green Dimming, From dark to light
CH11	000-255	3# Blue Dimming, From dark to light
CH12	000-255	4# Red Dimming, From dark to light
CH13	000-255	4# Green Dimming, From dark to light
CH14	000-255	4# Blue Dimming, From dark to light
CH15	000-255	5# Red Dimming, From dark to light



	056-065	
	066-075	
	076-085	
	086-095	
	096-105	
	106-115	
	116-125	
	126-135	
	136-145	Jump effect 01
	146-155	Jump effect 02
	156-165	Jump effect 03
	166-175	Jump effect 04
	176-185	Jump effect 05
	186-195	Jump effect 06
	196-205	Jump effect 07
	206-215	Jump effect 08
	216-225	Loops jump effect 01 to 08
	226-235	Yellow shade effect
	236-245	Loops red to yellow shade effect
	246-255	Sound active
CH4	000-255	Effects Speed from slow to fast
CH5	000-255	
CH6	000-255	Red Dimming, From dark to light
CH7	000-255	Green Dimming, From dark to light
CH8	000-255	Blue Dimming, From dark to light

9 Channels Mode:

Channel	DMX Value	Function
CH1	000-255	1-6# Red Dimming, From dark to light
CH2	000-255	1-6# Green Dimming, From dark to light
CH3	000-255	1-6# Blue Dimming, From dark to light
CH4	000-255	7-12# Red Dimming, From dark to light
CH5	000-255	7-12# Green Dimming, From dark to light



CH6	000-255	7-12# Blue Dimming, From dark to light
CH7	000-255	13-18# Red Dimming, From dark to light
CH8	000-255	13-18# Green Dimming, From dark to light
CH9	000-255	13-18# Blue Dimming, From dark to light

18 Channels Mode:

Channel	DMX Value	Function
CH1	000-255	1-3# Red Dimming, From dark to light
CH2	000-255	1-3# Green Dimming, From dark to light
CH3	000-255	1-3# Blue Dimming, From dark to light
CH4	000-255	4-6# Red Dimming, From dark to light
CH5	000-255	4-6# Green Dimming, From dark to light
CH6	000-255	4-6# Blue Dimming, From dark to light
CH7	000-255	7-9# Red Dimming, From dark to light
CH8	000-255	7-9# Green Dimming, From dark to light
CH9	000-255	7-9# Blue Dimming, From dark to light
CH10	000-255	10-12# Red Dimming, From dark to light
CH11	000-255	10-12# Green Dimming, From dark to light
CH12	000-255	10-12# Blue Dimming, From dark to light
CH13	000-255	13-15# Red Dimming, From dark to light
CH14	000-255	13-15# Green Dimming, From dark to light
CH15	000-255	13-15# Blue Dimming, From dark to light
CH16	000-255	16-18# Red Dimming, From dark to light
CH17	000-255	16-18# Green Dimming, From dark to light
CH18	000-255	16-18# Blue Dimming, From dark to light

54 Channels Mode:

Channel	DMX Value	Function
CH1	000-255	1# Red Dimming, From dark to light
CH2	000-255	1# Green Dimming, From dark to light
CH3	000-255	1# Blue Dimming, From dark to light
CH4	000-255	2# Red Dimming, From dark to light
CH5	000-255	2# Green Dimming, From dark to light
CH6	000-255	2# Blue Dimming, From dark to light



CH7	000-255	3# Red Dimming, From dark to light
CH8	000-255	3# Green Dimming, From dark to light
CH9	000-255	3# Blue Dimming, From dark to light
CH10	000-255	4# Red Dimming, From dark to light
CH11	000-255	4# Green Dimming, From dark to light
CH12	000-255	4# Blue Dimming, From dark to light
CH13	000-255	5# Red Dimming, From dark to light
CH14	000-255	5# Green Dimming, From dark to light
CH15	000-255	5# Blue Dimming, From dark to light
CH16	000-255	6# Red Dimming, From dark to light
CH17	000-255	6# Green Dimming, From dark to light
CH18	000-255	6# Blue Dimming, From dark to light
CH19	000-255	7# Red Dimming, From dark to light
CH20	000-255	7# Green Dimming, From dark to light
CH21	000-255	7# Blue Dimming, From dark to light
CH22	000-255	8# Red Dimming, From dark to light
CH23	000-255	8# Green Dimming, From dark to light
CH24	000-255	8# Blue Dimming, From dark to light
CH25	000-255	9# Red Dimming, From dark to light
CH26	000-255	9# Green Dimming, From dark to light
CH27	000-255	9# Blue Dimming, From dark to light
CH28	000-255	10# Red Dimming, From dark to light
CH29	000-255	10# Green Dimming, From dark to light
CH30	000-255	10# Blue Dimming, From dark to light
CH31	000-255	11# Red Dimming, From dark to light
CH32	000-255	11# Green Dimming, From dark to light
CH33	000-255	11# Blue Dimming, From dark to light
CH34	000-255	12# Red Dimming, From dark to light
CH35	000-255	12# Green Dimming, From dark to light
CH36	000-255	12# Blue Dimming, From dark to light
CH37	000-255	13# Red Dimming, From dark to light
CH38	000-255	13# Green Dimming, From dark to light
CH39	000-255	13# Blue Dimming, From dark to light